
# Tolomeo Faretto LED - 3000K - without switch

# Michele De Lucchi Giancarlo Fassina



# IP20 😩 🌃 [A]



### **LUMINAIRE**

- Watt: **6W** 

- Voltage: 220V-240V

- Delivered lumen output: **671lm** 

- CCT: **3000K**- Efficiency: **100%** 

- Efficacy: **111.77lm/W** 

- CRI: **90** 

## **DESCRIPTION**

Icon of Italian design and the result of the brainchild of designers Michele De Lucchi and Giancarlo Fassina, the Tolomeo lamp was launched on the market in 1987. It embodies the perfect balance between functionality and aesthetics.

In the Faretto version, the head of the Tolomeo lamp is fixed directly to a wall mount and is free to move in any direction just like in the iconic table lamp version. Controlled with the dimmer placed on the head or on the frame, it becomes a useful instrument of light for private spaces but also for work and hospitality environments.

#### **FEATURES**

Product Code: A044650
Colour: Aluminium
Installation: Wall
Material: Aluminium

- Series: **Design Collection** 

- design by: Michele De Lucchi, Giancarlo Fassina

#### **DIMENSIONS**

Height: 230 mmDepth: 250 mmGlow Wire Test: 750°

## **SOURCES INCLUDED**

Category: LedNumber: 1Watt: 5,5W

- Color temperature (K): 3000K

- CRI: **90** 

