

m o o o i

NomNom Light

ODIN VISSER




Can. Not. Resist! The NomNom Light by Odin Visser is a contemporary lighting design that puts a smile on your face and a tingle in your belly. This modestly sized suspension light is the perfect example of the art of omission, while remaining distinctive. Two straight lines and a sphere that create the illusion of two chopsticks holding something delicious. As a stand-alone, there's no way around NomNom's playful elegance, but when multiplied in a bundle or in a row, it's simply irresistible. The NomNom Light makes us hungry for more! And with six colours to choose from, there's always a new flavour to try out.

Detailing



The NomNom Light is compatible with our Wireless Wall Switch, for quick and easy dimming that gives you full control over the light output.


Colours



Blossom



Ginger



Indigo



Nori



Ruby



Wasabi

NomNom Light / NomNom Light 20

Dimensions

22cm | 8.7"



Product

WIDTH 22cm | 8.7"
HEIGHT 75cm | 29.5"
DEPTH 20cm | 7.9"
WEIGHT NETTO 1kg | 2.2lbs

Packaging

WIDTH 26cm | 10.2"
HEIGHT 26cm | 10.2"
CUBAGE 0.05m³ | 1.86ft³
LENGTH 78cm | 30.7"
WEIGHT 3.5kg | 7.72lbs

Technical CE / UL

MATERIAL
Anodized aluminium frame with a glass sphere

ENERGY LABEL
E

LIGHTSOURCE TYPE
LED

NUMBER OF LIGHTSOURCES
1

DIAMETER SHADE
20cm | 7.9"

FREQUENCY
50/60

LIFETIME
50000 hours

CABLE LENGTH
250cm | 98.4"

CANOPY
Pebble III Black, ABS

CHROM Y
0.3973

CRI
91

INSTALLATION REQUIRED
Yes

LIGHTSOURCE INCLUDED
Yes

SHAPE
Globe

INPUT VOLTAGE
110-270V

MAX POWER CONSUMPTION
8W

CABLE COLOUR
Black

SWITCH
No

CHROM X
0.4443

COLOUR TEMPERATURE
2800 K (max)

LIGHT DIRECTION
All directions

LIGHT OUTPUT

637 lm

**DIMMING & LIGHTING CONTROL**

Wireless Wall Switch (dimmer), Mains / ELV dimming is not possible, DALI dt6, Push / Pulse dim on Line Voltage, Smart Home Integration (Zigbee)

See last page for more information about the dimming possibilities.

Dimming & Lighting Control

Mains / ELV dimming is not possible

Mains and/or ELV dimming is not possible. The wireless wall switch is advised for dimming in this case.

Compatible models: NomNom Light 20 CCC, NomNom Light 20 CE, NomNom Light 20 UL

Wireless Wall Switch (dimmer)

With our Wireless Wall Switch, you'll have full control over your Moooi lighting design with one touch. Our Wireless Wall Switch comprises two components, a wall switch and radio device to put in the canopy of your Moooi lighting design. The Wall Switch can also be integrated in existing System 55 (i.e. Gira and Jung) or Decora style wall switches. Once the radio device is installed you will also have the possibility to control your light fixture with the Casambi App available in the Google Play and Apple app store. Within moments you can enjoy full and fluent dimming, all the way to dark.

Compatible models: NomNom Light 20 CE, NomNom Light 20 UL

DALI dt6

The luminaire is dimmable by integrating it into a DALI network. This is an universal and professional standard in home automation systems with endless control possibilities and ease. We advise to hire a professional to integrate the luminaire into your DALI network.

Compatible models: NomNom Light 20 CE, NomNom Light 20 UL

Push / Pulse dim on Line Voltage

The luminaire is dimmable by using an external momentary switch or pushbutton switch. The switch is usually mounted on an existing wall socket. In some cases a Phase or Control wire needs to be added to your home's wiring. The switch should be suitable for use with line voltage and of the type 'normal off - momentary on'. The luminaire dims perfectly when the switch makes and holds contact. A short press switches between on and off.

Compatible models: NomNom Light 20 CE, NomNom Light 20 UL

Smart Home Integration (Zigbee)

By adding a Zigbee converter this light fixture can seamlessly integrate into a Zigbee 3.0-based smart home network, such as Philips Hue, Amazon Alexa, Google Home, Ikea Tradfri and Homey. This integration allows for wireless control and compatibility with other smart home systems, without the need to change your home's wiring. To enable this, simply add a Zigbee converter to your luminaire. We recommend the Sunricher Zigbee to Dali

Converter for its reliability and compatibility with the US 110 voltage or the Osram 4062172044776 Zigbee 3.0 DALI Converter LI for 210-220V Please note that this converter is sold by third-party vendors and not directly by Moooli and this should be installed by a professional electrician.

Compatible models: NomNom Light 20 CE, NomNom Light 20 UL
